



**BUREAU
VERITAS**

Certificate of compliance

Applicant: SolaX Power Network Technology (Zhe jiang) Co., Ltd.
No.288 Shizhu Road, Tonglu Economic Development Zone,
Dongxing District 311500, Tonglu City, Zhejiang Province
China

Product: Photovoltaic (PV) inverter

Model: X3-50K-TL, X3-60K-TL

Use in accordance with regulations:

Automatic disconnection device with three-phase mains surveillance in accordance with EN 50549-1:2019 for photovoltaic systems with a three-phase parallel coupling via an inverter in the public mains supply. The automatic disconnection device is an integral part of the aforementioned inverter.

Applied rules and standards:

EN 50549-1:2019

Requirements for parallel connection of installations with distribution networks - Part 1: Connection to an LV distribution network - Production of installations up to and including Type B

- 4.4 Normal operating range
- 4.5 Immunity to disturbances
- 4.6 Active response to frequency deviation
- 4.7 Power response to voltage variations and voltage changes
- 4.8 EMC and power quality
- 4.9 Interface protection
- 4.10 Connection and starting to generate electrical power
- 4.11 Ceasing and reduction of active power on set point
- 4.13 Requirements regarding single fault tolerance of interface protection system and interface switch

EN 50438:2013

Requirements for micro-generating plants to be connected in parallel with public low-voltage distribution networks

At the time of issue of this certificate the safety concept of an aforementioned representative product corresponds to the valid safety specifications for the specified use in accordance with regulations.

Report number: PV200629N001-1

Certificate number: U20-0765

Certification Program: NSOP-0032-DEU-ZE-V01

Date of issue: 2020-09-24

Certification body



Thomas Lammel



Certification body Bureau Veritas Consumer Products Services Germany GmbH accreditation to DIN EN ISO/IEC 17065

A partial representation of the certificate requires the written approval of Bureau Veritas Consumer Products Services Germany GmbH



BUREAU
VERITAS

Annex to the EN 50549-1 certificate of compliance No. U20-0765

Appendix

Extract from test report according to EN 50549-1 No. PV200629N001-1

Type Approval and declaration of compliance with the requirements of EN 50549-1.

| | |
|----------------------------------|--|
| Manufacturer / applicant: | SolaX Power Network Technology (Zhe jiang) Co., Ltd. No.288 Shizhu Road, Tonglu Economic Development Zone, Dongxing District 311500, Tonglu City, Zhejiang Province China |
|----------------------------------|--|

| | | |
|-----------------------------------|-----------------------|------------------|
| Micro-generator Type | Photovoltaic inverter | |
| | X3-50K-TL | X3-60K-TL |
| MPP DC voltage range [V] | 540-850 | |
| Input DC voltage range [V] | 200-1100 | |
| Input DC current [A] | Max. 33/33/22/22 | Max. 33/33/33/33 |
| Output AC voltage [V] | 3/N/PE, 230/400, 50Hz | |
| Output AC current [A] | Max. 83 | Max. 92 |
| Output power [VA] | 55,0 | 66,0 |

| | |
|-------------------------|--------|
| Firmware version | 600101 |
|-------------------------|--------|

| | |
|----------------------------|-------------------------|
| Measurement period: | 2020-03-02 - 2020-05-20 |
|----------------------------|-------------------------|

Description of the structure of the power generation unit:
 The power generation unit is equipped with a PV and line-side EMC filter. The power generation unit has no galvanic isolation between DC input and AC output. Output switch-off is performed with single-fault tolerance based on two series-connected relays in each line and neutral. This enables a safe disconnection of the power generation unit from the network in case of error.



BUREAU
VERITAS

Annex to the EN 50549-1 certificate of compliance No. U20-0765

Appendix

Extract from test report according to EN 50549-1

No. PV200629N001-1

Setting of the interface protection:

| Parameter | Max. disconnection time | Min. operate time | Trip value |
|--|--|-------------------|--------------------|
| Over voltage (stage 1) ^a | 3s | - | 230V +10% (253V) |
| Over voltage (stage 2) | 0,2s | 0,1s | 230V +15% (264,5V) |
| Under voltage | 1,5s | 1,2s | 230V -15% (195,5V) |
| Over frequency | 0,5s | 0,3s | 50Hz +4% (52Hz) |
| Under frequency | 0,5s | 0,3s | 50Hz -5% (47,5Hz) |
| Reconnection settings for voltage (normal operational startup) | $0,85V_n (195,5V) \leq V \leq 1,10V_n (253V)$ | | |
| Reconnection settings for frequency (normal operational startup) | $49,5Hz \leq f \leq 50,2Hz$ | | |
| Reconnection time (normal operational startup) | $\geq 60s$ | | |
| Reconnection settings for voltage (automatic reconnection after tripping) | $0,85V_n (195,5V) \leq V \leq 1,10V_n (253V)$ | | |
| Reconnection settings for frequency (automatic reconnection after tripping) | $49,5Hz \leq f \leq 50,2Hz$ | | |
| Reconnection time (automatic reconnection after tripping) | $\geq 60s$ | | |
| Active power gradient after reconnection | 10% P _E max / per minute | | |
| Active power delivery at under frequency | electronic inverter, no active power reduction | | |
| Power response to over frequency (frequency / droop s) | 50,2Hz / 5% | | |
| Permanent DC-injection | 0,5% of rated inverter output current or 20mA | | |
| Rate of change of frequency (ROCOF) | 2Hz/s | | |
| Loss of mains according EN 62116 (LoM) | 2,0s | | |

Note:

^a Over voltage – stage1: 10 min-mean-value corresponding to EN 50160.

Default interface setting according to EN 50438:2013 are used.

The settings of the interface protection are password protected adjustable.

In case the above stated generators are used with an external protection device, the protection settings of the inverters are to be adjusted according to the manufacturer's declaration.

The above stated generators are tested according to the requirements in the EN 50549-1:2019. Any modification that affects the stated tests must be named by the manufacturer/supplier of the product to ensure that the product meets all requirements of the EN 50549-1:2019.